




# LD 11500 SS

powered by Lombardini 25LD425

## Model LD 11500 SS



1. General Details		
Frequency	50 Hz	
Voltage	230 V	
Max Power	<b>11</b>	KVA
Continuous power	10	KVA
Power factor cos $\phi$	0,8	
Max Power	8,8	KWe
Continuous power	8,0	KWe
2. Petrol driven engine		
Make and model	<b>Lombardini</b>	<b>25LD425</b>
rpm	3000	
Max power at 3600 rpm	17,7	HP
Cooling system	Air	
Cylinders	2	
Displacement (cm <sup>3</sup> )	851	

<b>3. Alternator</b>						
Make and model	<b>LINZ</b>	<b>E1C11M B</b>				
Max power	<b>12,5</b>	<b>kVA</b>				
Continuous power	<b>11,3</b>	<b>kVA</b>				
<b>4. Starting system</b>						
Electric						
<b>5. Standard Equipment</b>						
<ul style="list-style-type: none"> <li>✓ Soundproof canopy</li> <li>✓ Vibration dampers</li> <li>✓ Low oil level protection</li> <li>✓ Exhaust gas silencer</li> <li>✓ Air filter</li> <li>✓ Integrated fuel tank</li> <li>✓ Distribution control panel with output sockets with circuit breaker</li> <li>✓ Manual control panel QM107</li> <li>✓ Lifting eye</li> </ul>						
<b>6. Electric Panels</b>						
<b>QM 107 STANDARD</b>				<b>ACP 0411</b> available for genset with electronic starting system		
 <ul style="list-style-type: none"> <li>✓ Starter key</li> <li>✓ 16A Single Phase socket 3P</li> <li>✓ 32A Single phase socket 3P</li> <li>✓ Circuit breaker</li> <li>✓ Power Terminal Board</li> <li>✓ Emergency stop button</li> <li>✓ Hour counter</li> <li>✓ Voltmeter, frequencymeter</li> <li>✓ Fuel warning light</li> </ul>				 <ul style="list-style-type: none"> <li>✓ Control unit</li> <li>✓ Frequency and voltage indicators</li> <li>✓ Generating set/mains supply contractors</li> <li>✓ Automatic battery charger</li> </ul>		
<b>7. Logistic Information</b>						
	<b>Model</b>	<b>Fuel tank (litres)</b>	<b>Weight (Kgs)</b>	<b>Dimensions (cm)</b>		
				<b>L</b>	<b>W</b>	<b>H</b>
	Tecnosilent LD11500SS	20	220	107	56	92
<b>8. Fuel consumption</b>						
litres/hour at 75% load		2,3	approx			
<b>9. Marking</b>						
Label showing the general data of the genset (voltage, power, frequency). engine model with serial number, alternator model. TECNOGEN LOGO						
<b>10. Operating manuals</b>						
English. Other languages available on request.						